


The **NOMAD POWER PRO 12 XL** is a lithium-based power pack that combines **3 functions**:

- **Booster for 12 V vehicles** (*motorbike, car, SUV, van, tractor, boat*).
- **Autonomous power supply** for all kinds of electrical appliances.
- **Emergency lamp**.

LITHIUM BATTERY BOOSTER

Its **lithium** battery ($LiFePO_4$) gives it an exceptional power-to-size ratio (*starting current : 1000 A*).

It starts vehicles equipped with a discharged 12 V battery (*liquid, gel, AGM, Start&Stop*) in a few seconds ( *do not start Lithium $LiFePO_4$ batteries with this booster, battery voltages not compatible*).

START												
12 V PETROL & DIESEL												

SAFETY START

All safety features are integrated into the product to protect both the battery and the vehicle's electronic equipment:

- Anti-spark technology,
- Short circuit protection,
- Reverse polarity protection.
- Protection against excessive starting currents,
- Protection against booster temperature increases.

MOBILE ENERGY SOURCE

Its very powerful storage capacity (*8 Ah*) brings comfort and tranquility to the daily need to stay connected (*phone, tablet, computer*).

Equipped with:

- **2 USB 5 V - 2.1 A** ports for charging smartphone, tablet, GPS, etc.
- **1 output port 12 V - 3.5 A**, ideal for powering a 12 V electrical appliance (*cool box, TV, fan, etc.*)

HIGH BRIGHTNESS ASSIST LAMP

Auxiliary light (*28 leds*) with 3 lighting modes: normal, strobe, SOS.

LCD DISPLAY

The **NOMAD POWER PRO 12 XL** is equipped with an LCD display that gives information on:

- the % of charge of the internal battery.
- the different input and output ports used.



Colour LCD display



Supplied with accessories:



Charger 230 Vac / 18 Vdc



Strap



Cigarette lighter charger



3 in 1 cable

STARTING						EQUIPMENT					INPUT / OUTPUT				POWER BANK	LED	DIMENSIONS			
Lithium		I				J3s	SMART CABLE			CABLES			INPUT	OUTPUT						
Capacity per cell	Full charge	Start	Cranking CC	Peak Battery	USB-C					MICRO USB Type B	Lightning	12V		15V						
8 Ah 118.4 Wh	10 h	1000 A	1800 A	3000 A	22000 J							18V-2A	2	5V-2.1A	3.5A	—		3 modes : Light SOS SPOT	27.8 x 11 x 27.4	5.6